



Start im ersten Quartal 2026 geplant

AW-RP200GJ

Die Remote-Kamerasteuerungseinheit der nächsten Generation revolutioniert die Arbeitsabläufe des Benutzers. Aufbauend auf der für ihre hervorragende Bedienbarkeit bekannten Vorgängerversion AW-RP150GJ, bringt die AW-RP200GJ leistungsstarke neue Funktionen mit: Dazu gehören eine praktische Makro-Funktion, mit der sich komplexe Kamerabewegungen einfach ausführen lassen, sowie zwei Joysticks (links und rechts) für eine besonders flexible Steuerung. Diese Weiterentwicklungen optimieren die Performance des Controllers für den Einsatz in Multi-Kamera-Produktionen, selbst in großen Produktionsumgebungen, und unterstützen so die Erstellung von Video-Content mit höherem Mehrwert.

Key Features

20 Multifunktions-Tasten für Kameraauswahl, Preset-Abruf und Makro-Ausführung

Erster Remote-Kamera-Controller von Panasonic mit Makro-Funktion

Praktischer zweiter Joystick auf der linken Seite (ergänzend zum Haupt-Joystick rechts für Pan, Tilt, Zoom oder Fokus-Steuerung)

Panasonic



AW-RP200GJ

<https://eu.connect.panasonic.com/de/de/broadcast-proav/aw-rp200gj>

General -> Power Requirements	DC 12 V
General -> PoE	PoE++ IEEE802.3bt standard : DC 42 V to 57 V
General -> Weight	Approx. 3.5 kg (7.72 lb)
General -> Dimensions	364 mm x 178 mm x 245 mm (14-11/32 inches x 7 inches x 9-21/32 inches) (excluding protrusions)
Input Connector -> DC IN	DC 12 V IN, XLR 4-pin
Input Connector -> 3G SDI IN	SMPTE424M/SMPTE292M/75Ω (BNC×1)
Output Connector -> 3G SDI OUT	SMPTE424M/SMPTE292M/75Ω (BNC×1)
Input/Output Connector -> LAN (IP CONT)	LAN (RJ-45)
Input/Output Connector -> LAN (SERIAL CONT 1-3)	RS-422 x3 (RJ-45)
Input/Output Connector -> TALLY / GPIO 1	GPIO x2 (DSUB 25-pin)
Input/Output Connector -> USB Port	USB Type-A/Type-C (USB2.0)
Input/Output -> LCD Display	7-inch Touch Panel GUI Monitor (WVGA(800×480))
Connection Specifications -> No. of Connectable Cameras	200 (IP), 3 (RS-422)
Connection Specifications -> No. of Camera Selection Buttons	20
Memory -> Preset Memory	No. of memory presets 100 per camera
Memory -> Tracing Memory	Maximum of 10 settings per camera (CAM1 ~ 10)
Memory -> Macro Memory	No. of macros 100