

Pioneer Dj

A NEW HORIZON

DJM-A9

4-CHANNEL PROFESSIONAL DJ MIXER

- Stunningly clear sound quality
- Evolved playability
- Sound Color FX with world's first Center Lock
- Newly advanced Beat FX
- Expanded connectivity
- Enhanced mic section
- Dual independent headphone outputs and booth EQ
- Support for the Stagehand app and built-in Sound Check function
- Support for rekordbox and Serato DJ Pro
- DJM-REC app support for reliable recording
- Video and lighting app support



rekordbox

serato DJ Pro

DJM-A9

A NEW HORIZON

4-CHANNEL PROFESSIONAL DJ MIXER



SPECIFICATIONS

Input/Output Terminals	Inputs	DIGITAL x 4 (coaxial) LINE x 4 (RCA) PHONO x 4 (RCA) MIC x 2 (XLR & 1/4" TRS jack x 1, 1/4" TRS jack x 1)
	Outputs	MASTER x 2 (XLR x 1, RCA x 1) BOOTH x 1 (1/4" TRS jack) REC x 1 (RCA) DIGITAL MASTER x 1 (coaxial) PHONES x 4 (1/4" stereo jack x 2, 3.5-mm stereo mini jack x 2)
	USB	USB Type-A x 1 USB Type-B / USB Type-C x 2
	Others	SEND (1/4" TS jack) x 1 RETURN (1/4" TS jack) x 1 LAN terminal (100BASE-TX) x 1
Frequency Response		20 Hz – 40 kHz (LINE)
S/N Ratio		114 dB (USB, Digital IN) 88 dB (PHONO) 105 dB (LINE) 79 dB (MIC 1, MIC 2)
Total Harmonic Distortion		0.005 % (LINE-MASTER1)
Power Consumption		46 W
Maximum Dimensions (W x D x H)		407.4 x 458.3 x 107.9 mm (with the wireless antenna 140.7 mm) / 16.4" x 18.4" x 4.25" (with the wireless antenna 5.54")
Weight		10.2 kg / 22.5 lb
Accessories		Power cord Quick Start Guide Precautions for Use
Compatible Software		rekordbox, Serato DJ Pro, ShowKontrol, PRO DJ LINK Bridge

Bluetooth transmission distances are a guideline. Transmission distances may change depending on the surrounding environment.



Visit the official rekordbox website for its specifications: rekordbox.com




Visit the official Serato DJ Pro website for its specifications: serato.com

PRODUCT FEATURES

STUNNINGLY CLEAR SOUND QUALITY

The next-generation club sound comes from extensive development and fine-tuning of existing technology, plus brand-new components including ESS Technology 32-bit high-quality A/D and D/A converters in the channel section and outputs respectively.



NEWLY ADVANCED BEAT FX

A new color display helps you to quickly and accurately understand the status of the selected Beat FX, and it features lighting that corresponds with the X-Pad's horizontal arrangement, enabling more intuitive control with a simple finger slide. There are 14 Beat FX to play with including 3 new ones: Mobius, Triplet Fliter, and Triplet Roll.

EVOLVED PLAYABILITY

The DJM-A9 features increased spacing around the EQ knobs, bright LEDs in the channel section, optimized frequency response on the isolators, slicker channel faders than the DJM-900NXS2, plus the third-generation MAGVEL FADER crossfader.




ENHANCED MIC SECTION

The phantom powered input means you can connect a high-quality condenser mic directly to the DJM-A9, and there are 3 new microphone effects with a dedicated reverb effect so you can change the sound of your voice and hype up the crowd.

SOUND COLOR FX WITH WORLD'S FIRST CENTER LOCK

Turn on the brand-new Center Lock feature and, when you're using the popular Sound Color FX, each knob will stop turning when you reach the center position so you can't go too far and accidentally switch from the hi/low to the opposite parameter.



EXPANDED CONNECTIVITY AND DUAL INDEPENDENT HEADPHONE OUTPUTS

Connect 2 different PC/Mac systems at the same time thanks to the dual USB Type-B and USB Type-C ports (there are 2 of each) and route wireless audio to any channel via the Bluetooth input. The Multi I/O section has an independent channel selector, giving the DJM-A9 true send capabilities. There are dual headphone outputs too, each with their own cue buttons, volume knobs, and mix balance knobs, so you can monitor tracks independently from another DJ.

* Disclaimer: Specifications and price are subject to change. | * rekordbox™ is a trademark or registered trademark of AlphaTheta Corporation. | * PRO DJ LINK™ is a trademark of AlphaTheta Corporation. | * Serato DJ Pro is a registered trademark of Serato Limited. | * ShowKontrol is a trademark of TC Supply. | * TC SUPPLY is a trademark of Event Imaginering Group. | * Mixcloud is a registered trademark of Mixcloud Ltd. | * Twitch, the twitch Logo, the Glitch Logo, and/or Twitch TV are trademarks of Twitch Interactive, Inc. or its affiliates. | * Mac and macOS are trademarks of Apple Inc. registered in the U.S. and other countries. | * The Bluetooth® word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. and any use of such marks by AlphaTheta Corporation is under license. | Wi-Fi is a registered trademark of Wi-Fi Alliance®. | * Other product, technology, and company names, etc. mentioned herein are trademarks or registered trademarks of their respective owners.

